COMMUNICATION SYSTEM AND COMMUNICATION METHOD IN ACCORDANCE WITH EXTENDED PROTOCOL STANDARD

Background of the Invention

1. Field of the Invention

The present invention relates to a communication system and a communication method. More particularly, the present invention relates to a communication system for and a communication method of carrying out a communication in accordance with an extended protocol standard in which a certain protocol standard is extended.

2. Description of the Related Art

A packet transmission is widely used in data communication systems.

PPP (Point-to-Point Protocol) provides a standard method for transporting packets. In PPP, a packet is usually mapped into a frame, and PPP defines a format of the frame. PPP specifies that the transmitter inserts a control code into a frame for requesting a receiver to execute a function. The control code is referred to as a control sequence. The receiver refers to the control sequence and then executes the specified function.

An abort sequence is one of the control

sequences. The transmitter inserts an abort sequence into a frame to request the receiver to abort the frame. The receiver aborts the frame when detecting the abort sequence.

5   Fig. 1 shows a frame format of a packet transmission system based on PPP. Each of packets 101 is provided with an FCS (Frame Check Sequence) 102. The FCS holds a CRC (Cyclic Redundancy Check) code of the packet 101, which

10 is used for an error correction.

Flag sequences 103 are filled between the packets 101. The flag sequences 103 is constituted by one byte, and has a value "7Eh" of in the hexadecimal notation. Here, "h" is a

15 symbol indicative of a representation based on the hexadecimal number. The flag sequence 103 indicates the separation position between the two packets 101.

An abort sequence 104 is added to a packet

20 101a when the transmitter requests the receiver to abort the packet 101a. The receiver aborts the packet 101a when detecting the abort sequence 104.

PPP defines other control sequences besides the abort sequence.

25   However, a function undefined by the PPP is often desired to be executed in the packet transmission system. Therefore, extended control

sequences are often defined for executing the

undefined function. Hereinafter, a protocol

defining a control sequence undefined by the PPP

in addition to the control sequences defined by

5 the PPP is referred to as an extended PPP.

For example, a control sequence for a

function of transiently stopping a frame

transmission is not defined by PPP. The

transiently stopping is useful in adjusting a

10 transmission speed of a frame. Therefore, an

extended PPP is widely used in which an extended

control sequence is defined for providing a

function of transiently stopping a frame.

An interface apparatus operating on an

15 extended PPP is commercially available. An

advanced data sheet for the interface apparatus

is published by Lucent Technologies in August

1999, entitled "TDAT042G5 SONET/SDH 155/622/2488

Mbits/s Data Interface". The advanced data sheet

20 discloses an extended PPP on page 67.

Fig. 2 shows a frame format based on the

extended PPP. The transmitter operating on the

extended PPP divides one packet into a plurality

of partial packets 101b and 101c and transmits

25 them. Invalid sequences 105, indicative of a

transient stop of a frame transmission, are

filled between the partial packets 101b, and 101c.

The invalid sequences 105 are constituted by two bytes, and have a value of "7Dh, 20h". The invalid sequence is not defined by PPP.

The receiver operating on the extended PPP refers to the invalid sequence 105, and recognizes that the partial packets 101b, and 101c are the components of a single packet. The receiver reproduces the single packet from the partial packets 101b, and 101c.

However, the conventional packet transmission system has the following problem. In the packet transmission system, communications are carried out between unspecific transmitters and receivers. Thus, a receiver not operating on the extended PPP but on the original PPP may be used on the receiving side. The receiver may erroneously recognize the invalid sequences included in the received frame as a data to be received. This may result in that the receiver receives wrong data. That is, this may bring about the erroneous reception.

It is desirable to attain a communication apparatus for and a communication method of transmitting a signal in accordance with an extended standard in which a certain standard is extended, wherein if a receiver complying with the extended standard receives the signal, a

function is attained correspondingly to the extended standard, and wherein even if the signal is received by a receiver complying with only an original standard, the communication apparatus

5 and the communication method do not bring about an erroneous reception.

Summary of the Invention

Therefore, an object of the present

10 invention is to provide a communication apparatus for and a communication method of transmitting a signal in accordance with an extended standard in which a certain standard is extended, wherein if a receiver complying with the extended standard

15 receives the signal, a function defined by the extended standard is attained, and wherein even if the signal is received by a receiver complying with only an original standard, the communication apparatus and the communication method do not

20 bring about an erroneous reception.

Another object of the present invention is to provide a communication apparatus for and a communication method of transmitting a signal in accordance with an extended standard in which PPP

25 is extended, wherein if a receiver complying with the extended standard receives the signal, a function is attained correspondingly to the

extended standard, and wherein even if the signal
is received by a receiver complying with only an
original PPP standard, the communication
apparatus and the communication method do not
5 bring about an erroneous reception.

Still another object of the present
invention is to provide a communication apparatus
for and a communication method of transmitting a
signal in accordance with an extended standard in
10 which PPP is extended and a transient stop
function of a packet transmission is carried out,
wherein if a receiver complying with the extended
standard receives the signal, the transient stop
function of the packet transmission is carried
15 out, and wherein even if the signal is received
by a receiver complying with only the PPP, the
communication apparatus and the communication
method do not bring about an erroneous reception.

Still another object of the present
20 invention is to provide a communication apparatus
for and a communication method of transmitting a
signal in accordance with an extended standard in
which PPP is extended and a transient stop
function of a packet transmission is carried out
25 when a transmission FIFO included in a
transmitter becomes at an underflow state,
wherein if a receiver complying with the extended

standard receives the signal, the transient stop
function of the packet transmission is carried
out, and wherein even if the signal is received
by a receiver complying with only the PPP, the
5   communication apparatus and the communication
method do not bring about an erroneous reception.

Still another object of the present
invention is to provide a communication apparatus
for and a communication method of transmitting a
10   signal in accordance with an extended standard in
which PPP is extended and a transmission speed of
a transmitter is reduced when a reception FIFO
included in a receiver has a fear of an overflow
state, wherein if a receiver complying with the
15   extended standard receives the signal, the
function of reducing the transmission speed is
carried out, and wherein even if the signal is
received by a receiver complying with only the
PPP, the communication apparatus and the
20   communication method do not bring about an
erroneous reception.

In order to achieve an aspect of the
present invention, a communication system is
composed of first and second communication units.
25   The first communication unit sends transmission
data, a control sequence, and an extended control
sequence. The control sequence is originally

defined by a protocol and includes an abort

sequence requesting for abortion of the

transmission data. The extended control sequence

is undefined by the protocol and is provided for

5   requesting an extended operation. The second

communication unit receives the transmission data,

the control sequence, and the extended control

sequence. The second communication unit executes

the extended operation in response to the

10   extended control sequence. The extended control

sequence includes the abort sequence.

The protocol may be PPP (Point-to-Point

Protocol), and the abort sequence may be

represented by "7D, 7E" in the hexadecimal

15   notation.

Preferably, the extended control sequence

consists of a plurality of the abort sequence.

The first communicating unit may divide the

transmission data into a plurality of divided

20   data, and sequentially transmits the plurality of

divided data to the second communication unit. In

this case, the second communicating system

preferably reproduces the transmission data from

the plurality of divided data in response to the

25   extended control sequence.

The first communication unit may include a

transmission high order layer, a transmission

FIFO, a transmission data processor. In this case, the transmission high order layer generates the transmission data. The transmission FIFO transiently stores the transmission data, and

5 sequentially outputs the transmission data. The transmission data processor reads the transmission data out of the transmission FIFO to transmit the transmission data to the second communication unit. The transmission data

10 processor divides the transmission data into a plurality of divided data when an underflow occurs in the transmission FIFO, and sequentially transmits the plurality of divided data to the second communication unit. The second

15 communication unit reproduces the transmission data from the plurality of divided data in response to the extended control sequence.

The first communication unit may include a CRC indicating unit, and a CRC calculator. In

20 this case, the CRC indicating unit outputs a CRC indication sequence as the extended control sequence for indicating a CRC (Cyclic Redundancy Check) method. The CRC calculator calculates a CRC code according to the CRC method and outputs

25 the CRC code to the second communication unit. The second communication unit executes a CRC on the transmission data in response to the CRC

indication sequence based on the CRC code
according to the CRC method.

The first communication unit may include an
operation test indicating unit outputting an
5 operation test indicating sequence as the
extended control sequence, and outputting test
data. In this case, the second communication unit
preferably executes an operation test based on
the test data in response to the operation test
10 indicating sequence.

The second communication unit may send a
predetermined signal to the first communication
unit in response to the extended control sequence.

In order to achieve another aspect of the
15 present invention, a communication system is
composed of first and second communication units.
The first communication unit transmits first
transmission data. The second communication unit
receives the first transmission data, and
20 transmits second transmission data, a control
sequence, and an extended control sequence to the
first communication unit. The control sequence is
originally defined by a protocol, and includes an
abort sequence requesting for abortion of the
25 second transmission data. The extended control
sequence is undefined by the protocol and
includes the abort sequence. The first

communication unit adjusts a rate of transmitting
the first transmission data in response to the
extended control sequence.

   The second communication unit may include a
5 reception FIFO. The reception FIFO receives and
stores the first transmission data. The extended
control sequence is generated in accordance with
a state of the reception FIFO.

   The first communication unit may divide the
10 first transmission data into a plurality of
divided data, and transmit the plurality of
divided data and another extended control
sequence to the second communication unit. In
this case, the second communicating system
15 preferably reproduces the first transmission data
from the plurality of divided data in response to
the another extended control sequence.

   In order to achieve still another aspect of
the present invention, a transmitter is composed
20 of a data receiver and a sending unit. The data
receiver receives a transmission data. The
sending unit sends the transmission data, a
control sequence and an extended control sequence.
The control sequence is originally defined by a
25 protocol, and includes an abort sequence
requesting for abortion of the transmission data.
The extended control sequence is undefined by the

protocol and is provided for requesting an
extended operation.

In order to achieve still another aspect of
the present invention, a receiver is composed of
5   a receiving unit, and an outputting unit. The
receiving unit receives a transmission data, a
control sequence, and an extended control
sequence. The control sequence is originally
defined by a protocol, and includes an abort
10 sequence requesting for abortion of the
transmission data. The extended control sequence
is undefined by the protocol and is provided for
requesting an extended operation. The outputting
unit outputs the received transmission data. The
15 receiving unit executes the extended operation in
response to the extended control sequence, and
the extended control sequence includes the abort
sequence.

In order to achieve still another aspect of
20 the present invention, a communication method
comprising:

sending transmission data;

sending a control sequence originally
defined by a protocol wherein the control
25 sequence includes an abort sequence requesting
for abortion of the transmission data;

sending an extended control sequence, which

is undefined by the protocol and is provided for

requesting an extended operation;

receiving the transmission data, the

control sequence, and the extended control

5   sequence; and

executing the extended operation in

response to the extended control sequence. The

extended control sequence includes the abort

sequence.

10

Brief Description of the Drawings

Fig. 1 shows a signal format of a signal in

accordance with PPP;

Fig. 2 shows a signal format of a signal

15   used in a conventional communication system;

Fig. 3 shows a configuration of a

communication system of a first embodiment

according to the present invention;

Fig. 4 shows a configuration of a PPP frame

20   signal 7a;

Fig. 5 shows a configuration of a PPP frame

signal 7a into which an abort sequence 24 is

inserted;

Fig. 6 shows a configuration of a PPP frame

25   signal 7a into which a transient stop sequence 25

and a packet completion sequence 26 are inserted;

Fig. 7 shows another configuration of the

PPP frame signal 7a into which the transient stop sequence 25 and the packet completion sequence 26 are inserted;

Fig. 8 shows still another configuration of the PPP frame signal 7a into which the transient stop sequence 25 and the packet completion sequence 26 are inserted;

Fig. 9 shows a configuration of a communication system of a second embodiment according to the present invention;

Fig. 10 shows a content of a PPP frame signal $37a_1$ into which a speed adjustment packet 51 and a speed adjustment sequence 52 are inserted;

Fig. 11 shows a content of a PPP frame signal $37a_1$ into which an extension function check sequence is inserted;

Fig. 12 shows a configuration of a communication system of a third embodiment according to the present invention;

Fig. 13 shows a content of a PPP frame signal 7a into which an FCS control packet 54 and a FCS control sequence 55 are inserted;

Fig. 14 shows a configuration of a communication system of a fourth embodiment according to the present invention; and

Fig. 15 shows a configuration of a PPP

frame signal 7a into which a test packet 55 and a test sequence 56 are inserted.

Description of the Preferred Embodiments

5   A communication system according to the present invention will be described below with reference to the attached drawings.

<u>First Embodiment</u>

10   Fig. 3 shows a communication system in a first embodiment of the present invention. The communication system in the first embodiment is provided with a transmission high order layer 1, a transmission framer 2, a transmission path 3, a

15 reception framer 4 and a reception high order layer 5.

          The transmission high order layer 1 provides packets to be transmitted. The transmission high order layer 1 transmits the

20 packets to the transmission framer 2 on a transmission packet signal 1a. Moreover, the transmission high order layer 1, if aborting the transmission of the packets, transmits an abort indication signal 1b indicative of the abort of

25 the packet transmission, to the transmission framer 2.

          The transmission framer 2 is composed of a

transmission FIFO 6, a transmission packet
processor 7, a scrambler 8 and a transmission
overhead processor 9.

The transmission FIFO 6 transiently
5 accumulates the packet transmitted from the
transmission high order layer 1. The transmission
FIFO 6 outputs the accumulated packet to the
transmission packet processor 7 on a transmission
packet signal 6a, in the input order.

10   Moreover, the abort indication signal 1b is
inputted to the transmission FIFO 6 from the
transmission high order layer 1. The transmission
FIFO 6 outputs an abort indication signal 6b
indicative of an abort of the packet transmission
15 to the transmission packet processor 7 when
receiving the abort indication signal 1b.

Moreover, the transmission FIFO 6 outputs
an underflow occurrence signal 6c when an
underflow occurs therein. The transmission FIFO 6
20 may be at the underflow state if a speed at which
the packets are inputted to the transmission FIFO
6 is smaller than a speed at which the packets
are outputted from the transmission FIFO 6. In
such a case, the transmission FIFO 6 outputs the
25 underflow occurrence signal 6c indicative of the
occurrence of the underflow to the transmission
packet processor 7.

The transmission packet processor 7 reads
out the packets from the transmission FIFO 6, one
byte at a time, at a predetermined timing. The
transmission packet processor 7 adds FCS's, flag
5   sequences and control sequences to the read
packets to generate a PPP frame signal 7a.

In detail, the transmission packet
processor 7 calculates CRC codes of the packets,
and generates the FCS's for holding the CRC codes,
10 and then adds to the packets.

Furthermore, the transmission packet
processor 7 inserts flag sequences between the
packets. The flag sequences are filled between
the two packets, and indicate a separation
15 between two packets. The flag sequences have a
value of "7Eh" in the hexadecimal notation.

The transmission packet processor 7 inserts
an abort sequence into the PPP frame signal 7a,
if the abort of the packet is indicated by the
20 abort indication signal 6b. The abort sequence is
the control sequence defined by the PPP, as
mentioned above. The abort sequence is a code of
two bytes, and its value is 7Dh, 7Eh.

Moreover, the transmission packet processor
25 7 inserts a transient stop sequence and a packet
completion sequence into the PPP frame signal 7a,
if the underflow occurs in the transmission FIFO

6. Here, the transient stop sequence is a code of
four bytes, and its value is 7Dh, 7Eh, 7Dh and
7Eh in which the abort sequence is repeated twice.
The packet completion sequence is a code of six

5 bytes, and its value is 7Dh, 7Eh, 7Dh, 7Eh, 7Dh,
and 7Eh in which the abort sequence is repeated
three times.

If the underflow occurs in the transmission
FIFO 6, the input of the packet to the

10 transmission packet processor 7 is transiently
stopped. The input of the packet to the
transmission packet processor 7 is resumed after
the escape of the transmission FIFO 6 from the
underflow state. That is, the packet is divided

15 into a plurality of portions and inputted to the
transmission packet processor 7. In this
description, the plurality of portions generated
by the division of the packet are referred to as
partial packets, respectively. The transmission

20 packet processor 7 inserts the transient stop
sequence into a portion immediately after the
partial packet, if the input of the packet is
stopped. Moreover, the transmission packet
processor 7 inserts the packet completion

25 sequence into a portion immediately after the
finally partial packet required to constitute the
packet.

Fig. 4 shows the content of the PPP frame signal 7a generated by the transmission packet processor 7. Fig. 4 shows the content of the PPP frame signal 7a if the abort of the packet is not indicated and the underflow does not occur in the transmission FIFO 6. The PPP frame signal 7a includes a packet 21. The packet 21 is the packet read from the transmission FIFO 6. An FCS 22 is added to the final portion of the packet 21. A CRC code of the packet 21 is recorded in the FCS 22. Flag sequences 23 are filled between the packets 21.

On the other hand, Fig. 5 shows the content of the PPP frame signal 7a if the abort of the packet is indicated by the abort indication signal 6b. As shown in Fig. 5, an abort sequence 24 is added to a rear portion of a packet 21a to be aborted.

Moreover, Fig. 6 shows the content of the PPP frame signal 7a if the underflow occurs in the transmission FIFO 6. Fig. 6 shows the content of the PPP frame signal 7a if one packet is divided into a plurality of partial packets 21b, 21c and 21d and inputted to the transmission packet processor 7.

The transmission packet processor 7 inserts a transient stop sequence 25 into a portion

immediately after the partial packets 21b when

the underflow occurs in the transmission FIFO 6.

The transient stop sequence 25 shows that the

transmission of the packet constituted by the

5   plurality of partial packets 21b, 21c and 21d is

transiently stopped. The reception framer 4

recognizes that the partial packet 21b is a part

of one packet and that the remaining portions are

sent after that, from the transient stop sequence

10 25.

Similarly, the transmission packet

processor 7 also inserts another transient stop

sequence 25 into a portion immediately after the

partial packet 21c if the underflow occurs in the

15 transmission FIFO 6 when the partial packet 21c

is inputted to the transmission packet processor

7.

The transmission packet processor 7 inserts

an FCS 22a into a portion immediately after the

20 final partial packet 21d. The FCS 22a records

therein a CRC code of one packet constituted by

the plurality of partial packets 21b, 21c and 21d.

Moreover, the transmission packet processor

7 inserts a packet completion sequence 26 into a

25 portion immediately after the FCS 22a. The packet

completion sequence 26 shows that the plurality

of partial packets 21b, 21c and 21d are all

transmitted. The reception framer 4 recognizes
that the partial packet 21d is the final partial
packet of the packet that is divided and
transmitted, from the packet completion sequence
5 26.

Both of the transient stop sequence 25 and
the packet completion sequence 26 are the control
sequences undefined by the PPP. However, both of
them include "7Dh, 7Eh" implying the abort
10 sequence. As described later, the fact that both
of the transient stop sequence 25 and the packet
completion sequence 26 include the "7Dh, 7Eh"
implying the abort sequence provides the effect
that even if a signal having the transient stop
15 sequence 25 and the packet completion sequence 26
is sent to a reception framer which does not
expect the reception of the transient stop
sequence 25 and the packet completion sequence 26,
an erroneous reception is never induced only if
20 the reception framer aborts the received partial
packet.

As mentioned above, the transmission packet
processor 7 generates the PPP frame signal 7a
while inserting the transient stop sequence 25 or
25 the packet completion sequence 26 into the
portion immediately after each of the partial
packets constituting the packet, if the underflow

occurs in the transmission FIFO 6.

The PPP frame signal 7a, generated by the transmission packet processor 7, is outputted to the scrambler 8. The scrambler 8 performs a

5 scramble process on the PPP frame signal 7a and generates a scramble signal 8a. The scrambler 8 outputs the scramble signal 8a to the transmission overhead processor 9.

The transmission overhead processor 9 adds

10 an overhead to the scramble signal 8a and generates a SONET/SDH frame 9a. The SONET/SDH frame 9a has a form defined by a SONET/SDH (Synchronous Optical Network/Synchronous Digital Hierarchy) standard. The overhead is a code to

15 control an optical communication defined by the SONET/SDH standard. The transmission overhead processor 9 outputs the SONET/SDH frame 9a through the transmission path 3 to the reception framer 4.

20 The reception framer 4 is the reception framer for carrying out the operations corresponding to the transient stop sequence 25 and the packet completion sequence 26 that are the control sequences undefined by the PPP. The

25 reception framer 4 has a reception overhead processor 10, a de-scrambler 11, a reception packet processor 12 and a reception FIFO 13.

The reception overhead processor 10 removes the overhead from the SONET/SDH frame 9a transmitted through the transmission path 3, and then reproduces a scramble signal 10a

5   substantially equal to the scramble signal 8a.

The de-scrambler 11 performs the scramble process on the scramble signal 10a, and reproduces a PPP frame signal 11a substantially equal to the PPP frame signal 7a.

10   The reception packet processor 12 reproduces the packet from the PPP frame signal 11a, and outputs to the reception FIFO 13 by using a reception packet signal 12a.

The reception packet processor 12

15   reproduces the packet as follows.

If the PPP frame signal 11a does not transmit the packet, the PPP frame signal 11a has a value 7Eh implying the flag sequence. The reception packet processor 12 detects that the

20   sequentially input PPP frame signal 11a has another value which is not 7Eh implying the flag sequence, and accordingly recognizes the start of the input of the packet.

Moreover, the reception packet processor 12

25   detects that the PPP frame signal 11a again returns to the value 7Eh implying the flag sequence, and thereby recognizes that the packets

are inputted to the end. The reception packet

processor 12 fetches the packets from the PPP

frame signal 11a and outputs to the reception

FIFO 13. The reception FIFO 13 outputs the

5   packets to the reception high order layer 5 in

turn.

At this time, the reception packet

processor 12 judges the two bytes immediately

before the flag sequence as FCS, and then judges

10 whether or not the packet is normally transmitted,

in accordance with the CRC code included in the

FCS.

If it is judged that the packet is not

normally transmitted, the reception packet

15 processor 12 outputs an error packet report

signal 12b indicative of an abort of the packet

to the reception FIFO 13. The reception FIFO 13

receiving the error packet report signal 12b

outputs a packet abort signal 13b indicative of

20 the abort of the packet to the reception high

order layer 5. The reception high order layer 5

aborts the received packet in accordance with the

packet abort signal 13b.

The reception packet processor 12, even if

25 the abort sequence is included in the PPP frame

signal 11a, outputs the error packet report

signal 12b to the reception FIFO 13, and commands

to abort the packet.

Moreover, the reception packet processor 12, if detecting the transient stop sequence from the PPP frame signal 11a, recognizes that the

5 received packet is constituted by a plurality of partial packets and its transmission is transiently stopped.

If detecting the transient stop sequence, the reception packet processor 12 does not judge

10 that the packets are inputted to the end, even if detecting the flag sequence in succession after the transient stop sequence. Thus, the calculation of the FCS is not carried out.

At this time, the reception packet

15 processor 12 outputs the input partial packets to the reception FIFO 13 in turn. Moreover, the reception packet processor 12 outputs an EOP hold indication signal 12c to the reception FIFO 13. Usually, the reception packet processor 12

20 sequentially transfers the data of a packet to high order layers, and sends a report of EOP (End Of Packet) to the high order layers after the output of the final data of the packet. However, the EOP must not be outputted in receiving a non-

25 final partial packet. Therefore, the reception packet processor 12 outputs to the reception FIFO 13 the EOP hold indication signal 12c intended so

as not to output the EOP in the non-final partial

packet, as for the divided packets. Since the EOP

hold indication signal 12c is outputted to the

reception FIFO 13, the EOP is reported with

5   regard to only the final partial packet.

In succession, the reception packet

processor 12 detecting the transient stop

sequence monitors whether or not the PPP frame

signal 11a includes the packet completion

10   sequence. The detection of the packet completion

sequence enables the reception packet processor

12 to recognize the completion of the input of

the final partial packet among the plurality of

partial packets into which the packet is divided.

15   The reception packet processor 12 detecting the

packet completion sequence judges the two bits

immediately before the packet completion sequence

as the FCS, and then judges whether or not the

packet is normally transmitted.

20   If it is judged that the packet is not

normally transmitted, the reception packet

processor 12 outputs to the reception FIFO 13 the

error packet report signal 12b indicative of the

abort of the packet.

25   Moreover, the reception packet processor 12,

if detecting the packet completion sequence,

stops the output of the EOP hold indication

signal 12c, and allows the reception FIFO 13 to
output the packet to the reception high order
layer 5.

The reception FIFO 13 transfers in turn the
5   packets received from the reception packet
processor 12, to the reception high order layer 5.
Moreover, the reception FIFO 13 responds to the
error packet report signal 12b, and outputs to
the reception high order layer 5 the packet abort
10 signal 13b indicative of the abort of the packet.

The reception high order layer 5 receives
the packet from the reception FIFO 13. Moreover,
the reception high order layer 5 aborts the
received packet in accordance with the packet
15 abort signal 13b.

As mentioned above, the transmission framer
2, if the transmission FIFO 6 included therein
becomes at the underflow state, uses the
transient stop sequence and the packet completion
20 sequence, and transmits the packet while carrying
out the transient stop. The reception framer 4
refers to the transient stop sequence and the
packet completion sequence, and normally receives
the packet transmitted while it is transiently
25 stopped. In the communication system of this
embodiment, the packet can be normally
transmitted and received even if the transmission

FIFO 6 becomes at the underflow state. Thus, in the communication system of this embodiment, it is not necessary to abort the packet even if the transmission FIFO 6 becomes at the underflow

5 state. That is, even if the transmission FIFO 6 becomes at the underflow state, the transmission high order layer 1 need not re-transmit the packet. Hence, in the communication system of this embodiment, there is no case that the

10 transmission efficiency is dropped because of the re-transmission of the packet since the transmission FIFO 6 becomes at the underflow state.

Here, let us consider the case that the

15 transmission framer 2 in this embodiment is connected to a reception framer which does not comply with the transient stop sequence and the packet completion sequence although it complies with the PPP. Even in this case, there is no case

20 that the reception framer receives the erroneous data and then transfers to the reception high order layer. This is because both of the transient stop sequence and the packet completion sequence include the 7Dh, 7Eh implying the abort

25 sequence. The reception framer, which does not expect the reception of the transient stop sequence and the packet completion sequence,

recognizes the transient stop sequence and the packet completion sequence as the abort sequence, and merely aborts the transmitted packet. Thus, there is no case that the reception framer that

5 does not comply with the transient stop sequence and the packet completion sequence receives the erroneous data.

In this embodiment, the transient stop sequence and the packet completion sequence may

10 have other values if they can satisfy the following three conditions.

(1) They include the abort sequence 7Dh, 7Eh.

(2) They do not include the control sequence defined by the PPP.

15 (3) The transient stop sequence and the packet completion sequence are different from each other.

For example, as shown in Fig. 7, the transient stop sequence can have "7Dh, 20h, 7Dh, 7Eh", and the packet completion sequence can have

20 "7Dh, 21h, 7Dh, 7Eh".

However, as described in the explanation of this embodiment, both of the transient stop sequence and the packet completion sequence are the repetitions of the abort sequence "7Dh, 7Eh".

25 So, it is desired that the numbers of respective repetitions are different from each other. This reason is as follows. That is, it is understood

that the abort sequence "7Dh, 7Eh" always

indicates the abort process in the case of the

packet communication system complying with the

PPP. Thus, at least an erroneous reception is

5   never induced in the case of the packet

communication system complying with the PPP.

Also, in this embodiment, it is possible

that the packet completion sequence is not added

to a portion behind the finally transmitted

10 partial packet 21d among the partial packets 21b,

21c and 21d constituting one packet, as shown in

Fig. 8. In this case, the reception packet

processor 12 recognizes that the partial packet

21d is the finally transmitted partial packet

15 among the partial packets 21b, 21c and 21d

constituting the one packet, since the transient

stop sequence is not added to the portion behind

the partial packet 21d. A signal to be

transmitted can be reduced since the packet

20 completion sequence is not added.

On the other hand, if a reception framer,

which does not comply with the transient stop

sequence although it complies with the PPP,

receives a signal having a signal format shown in

25 Fig. 8, the reception framer does not calculate

an entire CRC code of the partial packets 21b,

21c and 21d constituting the one packet when

calculating a CRC code, and it calculates a CRC

code of only the partial packet 21d. The CRC code

calculated on the basis of only the partial

packet 21d does not typically agree with the CRC

5   code calculated on the basis of the entire packet

composed of the partial packets 21b, 21c and 21d.

The CRC code calculated on the basis of only the

partial packet 21d does not agree with the CRC

code noted in the FCS. Thus, the data of the

10   partial packet 21d is aborted because of an FCS

error. In this way, even if the reception framer,

which does not comply with the transient stop

sequence although complying with the PPP,

receives the signal having the format shown in

15   Fig. 8, the erroneous reception is not usually

induced.

However, if the CRC code of the partial

packet 21d accidentally agrees with the CRC code

noted in the FCS 22a although this probability is

20   very low, the partial packet 21d is judged as a

single packet. Thus, if a packet transmission

system requiring high data reliability is

established, it is desirable to add the packet

completion sequence.

25

Second Embodiment

Fig. 9 shows a communication system in a

second embodiment according to the present
invention. The communication system in the second
embodiment is provided with transmission high
order layers 31_1, 31_2, a first framer 32, optical

5   transmission paths 33_1, 33_2, a second framer 34
and reception high order layers 35_1, 35_2.

The first framer 32 is composed of a
transmission FIFO 36_1, a transmission packet
processor 37_1, a communication speed controller

10   38_1, a scrambler 39_1, a transmission overhead
processor 40_1, a reception overhead processor 41_2,
a de-scrambler 42_2, a reception packet processor
43_2 and a reception FIFO 44_2.

The second framer 34 is composed of a

15   transmission FIFO 36_2, a transmission packet
processor 37_2, a communication speed controller
38_2, a scrambler 39_2, a transmission overhead
processor 40_2, a reception overhead processor 41_1,
a de-scrambler 42_1, a reception packet processor

20   43_1 and a reception FIFO 44_1.

The communication system in this embodiment
is configured such that if the underflow occurs
in the transmission FIFO 36_1 and the transmission
FIFO 36_2, the packet can be normally transmitted

25   and received. Moreover, the purpose of the
communication system in this embodiment is to
adjust the transmission speeds at which the

transmission packet processors 37_1, 37_2 transmit

the packet, and thereby protect the underflow

from occurring in the reception FIFO 44_1, 44_2.

The communication system in this embodiment will

5   be described below.

Here, the operations of the transmission

FIFO 36_2, the transmission packet processor 37_2,

the communication speed controller 38_2, the

scrambler 39_2, the transmission overhead processor

10   40_2, the reception overhead processor 41_2, the de-

scrambler 42_2, the reception packet processor 43_2

and the reception FIFO 44_2 that are mounted on the

route through which the packet is transmitted to

the reception high order layer 35_2 from the

15   transmission high order layer 31_2 are respectively

equal to the operations of the transmission FIFO

36_1, the transmission packet processor 37_1, the

communication speed controller 38_1, the scrambler

39_1, the transmission overhead processor 40_1, the

20   reception overhead processor 41_1, the de-scrambler

42_1, the reception packet processor 43_1 and the

reception FIFO 44_1 that are mounted on the route

through which the packet is transmitted to the

reception high order layer 35_1 from the

25   transmission high order layer 31_1. Therefore,

only the operations of the transmission FIFO

36_1, the transmission packet processor 37_1, the

communication speed controller 38_1, the scrambler 39_1, the transmission overhead processor 40_1, the reception overhead processor 41_1, the de-scrambler 42_1, the reception packet processor 43_1 and the

5   reception FIFO 44_1 that are mounted on the route through which the packet is transmitted to the reception high order layer 35_1 from the transmission high order layer 31_1 will be described below.

10   The operations of the transmission high order layer 31_1 and the transmission FIFO 36_1 are respectively equal to the operations of the transmission high order layer 1 and the transmission FIFO 36 in the first embodiment.

15   The transmission high order layer 31_1 generates a packet to be transmitted. The transmission high order layer 31_1 transmits the generated packet to the transmission FIFO 36_1 on a transmission packet signal $31a_1$. Moreover, the

20   transmission high order layer 31_1, if aborting the transmission in the course of the packet transmission, transmits an abort indication signal $31b_1$ indicative of the abort of the packet transmission, to the transmission FIFO 36_1.

25   The transmission FIFO 36_1 transiently accumulates the packets transmitted from the transmission high order layer 31_1. The

transmission FIFO 36_1 outputs the accumulated

packets to the transmission packet processor 37_1

by using a transmission FIFO $36a_1$, in the input

order.

5   Moreover, the abort indication signal $31b_1$

is respectively inputted to the transmission FIFO

36_1 from the transmission high order layer 31_1.

The transmission FIFO 36_1, when receiving the

abort indication signal $31b_1$, outputs an abort

10   indication signal $36b_1$ indicative of an abort of

the packet transmission to the transmission

packet processor 37_1, respectively.

Moreover, the transmission FIFO 36_1 outputs,

when the underflow occurs therein, outputs an

15   underflow occurrence signal $36c_1$ to the

transmission packet processor 37_1.

The transmission packet processor 37_1 reads

the packets from the transmission FIFO 36_1, one

byte at a time, at a predetermined timing. The

20   transmission packet processor 37_1 adds the FCS,

the flag sequence and the control sequence to the

read packet, and then generates a PPP frame

signal $37a_1$.

The transmission packet processor 37_1

25   calculates the CRC code of the packet read from

the transmission FIFO 36_1, and generates the FCS

for holding the CRC code, and then adds to the

packet. The transmission packet processor 37_1 inserts the flag sequence between the packets. Moreover, the transmission packet processor 37_1 inserts the abort sequence into the PPP frame

5   signal $37a_1$, if the abort of the packet is indicated by the abort indication signal $36b_1$.

Moreover, the transmission packet processor 37_1 inserts the above-mentioned transient stop sequence and the packet completion sequence into

10 the PPP frame signal $37a_1$, if the underflow occurs in the transmission FIFO 36_1.

The above-described operations of the transmission packet processor 37_1 are same as that of the transmission packet processor 7 contained

15 by the communication system in the first embodiment, and the detailed explanation is omitted.

In addition to the above-mentioned operations, the transmission packet processor 37_1

20 monitors a remaining amount of a memory region of the reception FIFO 44_2, and inserts a speed adjustment packet and a speed adjustment sequence into the PPP frame signal $37a_1$, in response to the remaining amount.

25   The reception FIFO 44_2 outputs the remaining amount of the memory region of the reception FIFO 44_2 to the transmission packet

processor 37_1 on an overflow indication signal

$44a_2$. The transmission packet processor 37_1

generates a speed adjustment information with

regard to a speed at which the second framer 34

5   transmits a packet, on the basis of the remaining

amount. Then, the transmission packet processor

37_1 generates a speed adjustment packet including

the speed adjustment information. That is, the

transmission packet processor 37_1 inserts the

10   speed adjustment packet and the speed adjustment

sequence indicative of the transmission of the

speed adjustment packet into the PPP frame signal

$37a_1$.

Fig. 10 shows a speed adjustment packet 51

15   and a speed adjustment sequence 52 that are

included in the PPP frame signal $37a_1$. As

mentioned above, the speed adjustment packet 51

has the speed adjustment information. The speed

adjustment sequence 52 is added to a portion

20   immediately after the speed adjustment packet 51.

The speed adjustment sequence 52 is a code of 8

bytes, and it is equal to that of the four

repetitions of the abort sequence. The speed

adjustment sequence 52 shows that the packet

25   immediately before is the speed adjustment packet

51. As described later, the speed adjustment

information included in the speed adjustment

packet 51 is sent to the second framer 34. The
second framer 34 adjusts a transmission speed of
a packet to be transmitted to the first framer 32,
on the basis of the speed adjustment information.

5   Here, the speed adjustment packet 51 and
the speed adjustment sequence 52 are not always
inserted between the packets to be transmitted.
It is also possible to transiently stop the
transmission of one packet, and then possible to
10   insert the speed adjustment packet 51 and the
speed adjustment sequence 52.

         The transmission packet processor 37_1 for
inserting the speed adjustment packet 51 and the
speed adjustment sequence 52 further adjusts the
15   transmission speed, in response to a transmission
speed control signal $38a_2$ outputted by the
communication speed controller 38_2. Here, the
transmission speed control signal $38a_2$ is the
signal for adjusting the transmission speed of
20   the transmission packet processor 37_1. The
generating process will be described later.

         Actually, the transmission packet processor
37_1 divides one packet to be transmitted, into a
plurality of partial packets, similarly to the
25   first embodiment. The transmission packet
processor 37_1, while inserting the transient stop
sequence or the packet completion sequence into a

portion immediately after the plurality of partial packets, transmits the PPP frame signal $37a_1$. The plurality of partial packets are transmitted at a predetermined temporal interval.

5 The transmission packet processor 37_1 adjusts the temporal interval to accordingly adjust an effective transmission speed.

The PPP frame signal $37a_1$ generated by the above-mentioned processes in the transmission

10 packet processor 37_1 is outputted to the scrambler 39_1. The operation of the scrambler 39_1 is similar to that of the scrambler 8 in the first embodiment. The scrambler 39_1 performs the scramble process on the PPP frame signal $37a_1$, and

15 generates a scramble signal $38a_1$. The scrambler 39_1 outputs the scramble signal $39a_1$ to the transmission overhead processor 39_1.

The transmission overhead processor 40_1 adds an overhead to the scramble signal $39a_1$ and

20 generates a SONET/SDH frame $40a_1$. The transmission overhead processor 40_1 outputs the SONET/SDH frame $40a_1$ through the transmission path 33_1 to the reception overhead processor 41_1 of the reception framer 34.

25 The reception overhead processor 41_1 removes the overhead from the SONET/SDH frame $40a_1$ transmitted through the transmission path 33_1, and

reproduces a scramble signal $41a_1$ substantially

equal to the scramble signal $39a_1$.

The de-scrambler 42_1 performs the de-

scramble process on the scramble signal $39a_1$

5 substantially equal to the scramble signal $39a_1$.

The reception packet processor 43_1, while

referring to the transient stop sequence and the

packet completion sequence, reproduces a packet

from the PPP frame signal $42a_1$ and outputs to the

10 reception FIFO 44_1. The reception FIFO 44_1

transfers the reproduced packet to the reception

high order layer 35_1. The process is similar to

the operation of the reception packet processor

12 included in the communication system of the

15 first embodiment, and the explanation is omitted.

Moreover, the reception packet processor

43_1 fetches the speed adjustment information from

the speed adjustment packet generated by the

transmission packet processor 37_1, and outputs to

20 the transmission speed controller 38_1 by using a

speed adjustment information signal $43a_1$. The

transmission speed controller 38_1, in accordance

with the speed adjustment information fetched

from the speed adjustment packet, generates a

25 transmission speed control signal $38a_1$, and

adjusts a transmission speed of the transmission

packet processor 37_2.

The communication system in this embodiment having the above-mentioned configuration protects the overflow from occurring in the reception FIFO 44_1, 44_2. The process for adjusting the

5   transmission speed of the packet transmitted to the second framer 34 from the first framer 32 and accordingly protecting the overflow from occurring in the reception FIFO 44_1 will be described below.

10   The packet generated by the transmission high order layer 31_1 is transmitted to and accumulated in the reception FIFO 44_1 of the second framer 34, while its transmission speed is adjusted by the transmission packet processor 37_1.

15   The remaining amount of the memory region of the reception FIFO 44_1 for accumulating the packet generated by the transmission high order layer 31_1 is sent to the transmission packet processor 37_2 by using an overflow indication signal $44a_1$. The

20   transmission packet processor 37_2, if judging that the remaining amount of the memory region of the reception FIFO 44_1 is small, generates a speed adjustment information having a content indicative of a command for making the

25   transmission speed slower.

        The transmission packet processor 37_2 transmits the speed adjustment sequence and the

speed adjustment packet including the speed
adjustment information to the reception packet
processor 43_2 in the first framer 32. The
reception packet processor 43_2 fetches the speed

5 adjustment information from the received speed
adjustment packet, and outputs to a transmission
speed controller 38_2 by using a speed adjustment
information signal $43a_2$. The transmission speed
controller 38_2, in accordance with this speed

10 adjustment information, generates a transmission
speed control signal $38a_2$, and then reduces the
transmission speed of the transmission packet
processor 37_1. Thus, the transmission speed of
the packet transmitted to the reception FIFO 44_2

15 is reduced to thereby protect the overflow from
occurring in the reception FIFO 44_1.

The similar process protects the overflow
from occurring in the reception FIFO 44_2.

As mentioned above, in the communication

20 system in this embodiment, the adjustment of the
transmission speed enables the overflow from
occurring in the reception FIFO 44_1, 44_2.

Here, let us suppose that a signal
including the speed adjustment packet and the

25 speed adjustment sequence is sent to a framer
that does not comply with the speed adjustment
packet and the speed adjustment sequence although

it complies with the PPP. As mentioned above, the speed adjustment sequence includes the abort sequence "7Dh, 7Eh". Thus, if the signal including the speed adjustment packet and the

5 speed adjustment sequence is inputted to the framer that does not comply with the speed adjustment packet and the speed adjustment sequence, the framer aborts the speed adjustment packet and the speed adjustment sequence. Hence,

10 the framer does not bring about the erroneous reception.

In the above mentioned communication system, in which packets are transferred between the two framers, one of the framers can check whether or

15 not the other framer operates on the basis of the extended standard.

The transmission packet processor 37_1 of the first framer 32 inserts an extended standard check sequence into the PPP frame signal $37a_1$ and

20 transmits. Fig. 11 shows an extended standard check sequence 53 inserted into the PPP frame signal 37a1. The extended standard check sequence 53 is the control sequence in which the abort sequence "7Dh, 7Eh" is repeated five times, as

25 shown in Fig. 11. The extended standard check sequence is transmitted to the second framer 34. The reception packet processor 43_1 of the second

framer 34 recognizes the transmission of the

extended standard check sequence. The reception

packet processor 43_1 recognizing the transmission

of the extended standard check sequence commands

5 the transmission packet processor 37_2 to transmit

the extended standard check sequence to the first

framer 32.

In the extended standard check sequence

transmitted by the transmission packet processor

10 37_2, the reception packet processor 43_2 of the

first framer 32 recognizes the transmission of

the extended standard check sequence. Since the

reception packet processor 43_2 receives an

extended standard sequence, the first framer 32

15 can check that the second framer 34 is the framer

complying with the extended standard. In

accordance with the similar processes, the second

framer 34 can also check that the first framer 32

is the framer complying with the extended

20 standard.

Here, let us suppose that a signal

including the extended standard sequence is sent

to a framer that does not comply with the

extended standard sequence although it complies

25 with the PPP. As mentioned above, the extended

standard sequence includes the abort sequence

"7Dh, 7Eh". Thus, if the signal including the

extended standard sequence is inputted to the framer which does not comply with the extended standard sequence, the framer aborts the extended standard sequence. Hence, also, the framer does

5   not bring about the erroneous reception.

In the second embodiment, the transient stop sequence, the packet completion sequence, the speed adjustment sequence and the extended standard check sequence may have other values if

10 they can satisfy the following three conditions.

(1)   They include the abort sequence 7Dh, 7Eh.

(2)   They do not include the control sequence defined by the PPP.

(3)   The transient stop sequence, the packet

15 completion sequence, the speed adjustment sequence and the extended standard check sequence are different from each other.

Third Embodiment

20   Fig. 12 shows a communication system in a third embodiment according to the present invention. The configuration of the communication system in this embodiment is substantially similar to that of the communication system in

25 the first embodiment. The communication system in the third embodiment has the configuration in which an FCS controller 14 is added to the

communication system in the first embodiment.

Associated with the addition of the FCS

controller 14, the operations of a transmission

packet processor 7 and a reception packet

5   processor 12 of the communication system in the

third embodiment are different in the following

points from those of the communication system in

the first embodiment.

The FCS controller 14 outputs an FCS

10   control signal 14a to the transmission packet

processor 7.   The transmission packet processor 7

changes a method of calculating an FCS to be

inserted into the PPP frame signal 7a, in

response to the FCS control signal 14a.   Moreover,

15   the transmission packet processor 7 inserts an

FCS control packet indicative of the FCS

calculation method, and an FCS control sequence

into the PPP frame signal 7a.

Fig. 13 shows an FCS control sequence 55

20   and an FCS control packet 54 that are inserted

into the PPP frame signal 7a.   The FCS control

packet 54 is the packet indicative of the FCS

calculation method.   The FCS control sequence 55

is inserted into a portion immediately after the

25   FCS control packet 54.   The FCS control sequence

55 is the control sequence in which the abort

sequences "7Dh, 7Eh" are repeated four times.   The

FCS control sequence 55 shows that the packet immediately before is the FCS control packet 54.

The FCS control sequence 55 and the FCS control packet 54 that are inserted into the PPP

5 frame signal 7a are sent to the reception packet processor 12 of the reception framer 4. The reception packet processor 12 detects the FCS control sequence 55, and fetches the FCS control packet 54 received immediately before. The

10 reception packet processor 12 changes the FCS calculation method for the FCS calculation method shown by the FCS control packet 54. The reception packet processor 12 calculates a CRC code of the packet received by it, in accordance with the

15 changed FCS calculation method. Moreover, the reception packet processor 12 judges whether or not the packet is normally received, from the CRC code stored in the FCS added to the packet and the CRC code of the received packet.

20 As mentioned above, the communication system in this embodiment can change the FCS calculation method, which is the function undefined by the PPP.

Here, let us suppose that a signal

25 including the FCS control packet and the FCS control sequence is sent to a framer that does not comply with the FCS control packet and the

FCS control sequence although it complies with the PPP. As mentioned above, the FCS control sequence includes the abort sequence 7Dh, 7Eh. Thus, if the signal including the FCS control

5 packet and the FCS control sequence is inputted to the framer which does not comply with the FCS control packet and the FCS control sequence, the framer aborts the FCS control packet and the FCS control sequence. Hence, the framer does not

10 bring about the erroneous reception.

In the third embodiment, the FCS control sequence may have another value if it can satisfy the following three conditions.

(1)   It includes the abort sequence 7Dh, 7Eh.

15 (2)   It does not include the control sequence defined by the PPP.

(3)   The transient stop sequence, the packet completion sequence and the FCS control sequence are different from each other.

20

Fourth Embodiment

Fig. 14 shows a communication system in a fourth embodiment according to the present invention. The configuration of the communication

25 system in this embodiment is substantially similar to that of the communication system in the first embodiment. The communication system in

the fourth embodiment has the configuration in which a test packet generator 15 is added to the communication system in the first embodiment. Associated with the addition of the test packet

5   generator 15, the operations of the transmission packet processor 7 and the reception packet processor 12 of the communication system in the fourth embodiment are different in the following points from those of the communication system in

10 the first embodiment.

The test packet generator 15 generates a test packet and outputs the test packet to the transmission packet processor 7 by using a test packet signal 15a. The transmission packet

15 processor 7 inserts the test packet included in the test packet signal 15a into the PPP frame signal 7a. Moreover, the transmission packet processor 7 inserts a test packet sequence into the PPP frame signal 7a, in a portion immediately

20 after the test packet.

Fig. 15 shows a test packet 56 and a test sequence 57 that are inserted into the PPP frame signal 7a. The test sequence 57 is inserted into a portion immediately after the test packet 56.

25 The test packet 56 is the control sequence in which the abort sequences "7Dh, 7Eh" are repeated four times. The test sequence 57 shows that the

packet immediately before is the test packet 56.

The test packet 56 and the test sequence 57 that are inserted into the PPP frame signal 7a is transmitted to the reception packet processor 12

5 of the reception framer 4. The reception packet processor 12 detects the test sequence 57 and fetches the test packet 56 transmitted immediately before. The reception packet processor 12 carries out an operation test in

10 accordance with the test packet 56.

As described above, the communication system in this embodiment can carry out the operation test of the reception packet processor 12, which is the function undefined by the PPP.

15 Here, let us suppose that a signal including the test packet and the test sequence is sent to a framer that does not comply with the test packet and the test sequence although it complies with the PPP. As mentioned above, the

20 test sequence includes the abort sequence 7Dh, 7Eh. Thus, if the signal including the test packet and the test sequence is inputted to the framer that does not comply with the test packet and the test sequence, the framer aborts the test

25 packet and the test sequence. Hence, the framer does not bring about the erroneous reception.

In the fourth embodiment, the test sequence

- 51 -

may have another value if it can satisfy the

following three conditions.

(1)   It includes the abort sequence 7Dh, 7Eh.

(2)   It does not include the control sequence

5 defined by the PPP.

(3)   The transient stop sequence, the packet

completion sequence and the test sequence are

different from each other.

The present invention provides a

10 communication apparatus for and a communication

method of transmitting a signal in accordance

with an extended standard in which a certain

standard is extended, wherein if a receiver

complying with the extended standard receives the

15 signal, a function defined by the extended

standard is attained, and wherein even if the

signal is received by a receiver complying with

only an original standard, the communication

apparatus and the communication method do not

20 bring about an erroneous reception.

The present invention provides a

communication apparatus for and a communication

method of transmitting a signal in accordance

with an extended standard in which PPP is

25 extended, wherein if a receiver complying with

the extended standard receives the signal, a

function is attained correspondingly to the

extended standard, and wherein even if the signal

is received by a receiver complying with only a

PPP standard, the communication apparatus and the

communication method do not bring about an

5   erroneous reception.

The present invention provides a

communication apparatus for and a communication

method of transmitting a signal in accordance

with an extended standard in which PPP is

10   extended and a transient stop function of a

packet transmission is carried out, wherein if a

receiver complying with the extended standard

receives the signal, the transient stop function

of the packet transmission is carried out, and

15   wherein even if the signal is received by a

receiver complying with only the PPP, the

communication apparatus and the communication

method do not bring about an erroneous reception.

The present invention provides a

20   communication apparatus for and a communication

method of transmitting a signal in accordance

with an extended standard in which PPP is

extended and a transient stop function of a

packet transmission is carried out when a

25   transmission FIFO included in a transmitter

becomes at an underflow state, wherein if a

receiver complying with the extended standard

receives the signal, the transient stop function

of the packet transmission is carried out, and

wherein even if the signal is received by a

receiver complying with only the PPP, the

5   communication apparatus and the communication

method do not bring about an erroneous reception.

The present invention provides a

communication apparatus for and a communication

method of transmitting a signal in accordance

10 with an extended standard in which PPP is

extended and a transmission speed is reduced when

a reception FIFO included in a transmitter

becomes at an overflow state, wherein if a

receiver complying with the extended standard

15 receives the signal, the function of reducing the

transmission speed is carried out, and wherein

even if the signal is received by a receiver

complying with only the PPP, the communication

apparatus and the communication method do not

20 bring about an erroneous reception.

Although the invention has been described

in its preferred form with a certain degree of

particularity, it is understood that the present

disclosure of the preferred form has been changed

25 in the details of construction and the

combination and arrangement of parts may be

resorted to without departing from the spirit and

the scope of the invention as hereinafter claimed.